

# IB04C520 INDUCTIVE SENSORS • NORM SWITCHING DISTANCE

sensor inductive, M4x0.5 22long, Flush, Sn: 0.6, 10-30V DC, PNP NO, Cable connector M12 0.15m PUR (Polyurethane), IP67, VA



## **MECHANICAL FEATURES**


	IV000197
Active area material of sensor	Polyoxymethylene (POM)
Ambient temperature	-25 °C 70 °C
Cable length	0.15 m
Degree of protection (IP)	IP67
Housing design	Cylinder, screw-thread
Housing material	Stainless steel (V2A)
Material of cable sheath	PUR (Polyurethane)
Max. tightening torque	0.8 Nm
Mechanical mounting condition for sensor	Flush
Pressure-proof	-
Sensor length	22 mm
Thread pitch	0.5 mm
Thread size, metric	4
ELECTRICAL FEATURES	
Cascadable	
Rated switching current	- 100 mA
Suitable for safety functions	100 IIIA
Supply voltage	10 V 30 V
Switching distance	0.6 mm
Switching frequency	3000 Hz
Type of electrical connection	Cable connector M12
Type of switching function	Normally open contact
Type of switching output	PNP
Voltage type	DC
With monitoring function of downstream devices	
Other	
Packaging dimensions	77.0mm x 25.0mm x 123.0mm
Shipping weight	0.04kg
Tariff code	85365019



### Classification

ipf product group	700
eClass 8.0	27270101
eClass 9.0	27270101
eClass 9.1	27270101
ETIM-5.0	EC002714
ETIM-6.0	EC002714
ETIM-7.0	EC002714

#### Connection



### **Dimensional drawing**

### Installation



Mounting / installation may only be carried out by a qualified electrician!





# Software

Any software, drivers or IODD files that may be required to operate your device can be downloaded free of charge from our homepage: www.ipf-electronic.com

#### Safety warnings

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information.

Never use these devices in applications where the safety of a person depends on their functionality.

LED lighting systems can generate intensive UV radiation, which can damage your eyes in case of improper use. The manufacturer cannot be held responsible for damages that result from improper use or connection.